


SWITCHING APPLICATION.
INTERFACE CIRCUIT AND DRIVER CIRCUIT APPLICATION

FEATURES


- With Built-in Bias Resistors.
- Simplify Circuit Design.
- Reduce a Quantity of Parts and Manufacturing Process.

EQUIVALENT CIRCUIT




BIAS RESISTOR VALUES

TYPE NO.	R1(k Ω)	R2(k Ω)
KRA566E	1	10
KRA567E	2.2	2.2
KRA568E	2.2	10
KRA569E	4.7	10
KRA570E	10	4.7
KRA571E	47	10
KRA572E	100	100



EQUIVALENT CIRCUIT (TOP VIEW)




MAXIMUM RATING (Ta=25°C)

CHARACTERISTIC		SYMBOL	RATING	UNIT
Output Voltage	KRA566E 572E	V_O	-50	V
Input Voltage	KRA566E	V_I	-10, 5	V
	KRA567E		-12, 10	
	KRA568E		-12, 5	
	KRA569E		-20, 7	
	KRA570E		-30, 10	
	KRA571E		-40, 15	
	KRA572E		-40, 10	
Output Current	KRA566E 572E	I_O	-100	mA
Power Dissipation		P_D *	200	mW
Junction Temperature		T_j	-55~150	°C
Storage Temperature Range		T_{stg}	-55~150	°C

* : Total Rating.

MARK SPEC

TYPE	KRA566E	KRA567E	KRA568E	KRA569E	KRA570E	KRA571E	KRA572E
MARK	P2	P4	P5	P6	P7	P8	P9









KRA566E~KRA572E

ELECTRICAL CHARACTERISTICS (Ta=25°C)







CHARACTERISTIC		SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Cut-off Current	KRA566E 572E	$I_{O(OFF)}$	$V_O=-50V, V_I=0$	-	-	-500	nA
DC Current Gain	KRA566E	G_I	$V_O=-5V, I_O=-5mA$	33	-	-	
	KRA567E		$V_O=-5V, I_O=-20mA$	20	-	-	
	KRA568E		$V_O=-5V, I_O=-10mA$	33	-	-	
	KRA569E		$V_O=-5V, I_O=-10mA$	30	-	-	
	KRA570E		$V_O=-5V, I_O=-10mA$	24	-	-	
	KRA571E		$V_O=-5V, I_O=-5mA$	33	-	-	
	KRA572E		$V_O=-5V, I_O=-5mA$	62	-	-	
Output Voltage	KRA566E	$V_{O(ON)}$	$I_O=-10mA, I_I=-0.5mA$	-	-	-0.3	V
	KRA567E		$I_O=-10mA, I_I=-0.5mA$	-	-0.1	-0.3	
	KRA568E		$I_O=-10mA, I_I=-0.5mA$	-	-	-0.3	
	KRA569E		$I_O=-10mA, I_I=-0.5mA$	-	-0.1	-0.3	
	KRA570E		$I_O=-10mA, I_I=-0.5mA$	-	-0.1	-0.3	
	KRA571E		$I_O=-10mA, I_I=-0.5mA$	-	-0.1	-0.3	
	KRA572E		$I_O=-5mA, I_I=-0.25mA$	-	-0.1	-0.3	
Input Voltage (ON)	KRA566E	$V_{I(ON)}$	$V_O=-0.3V, I_O=-20mA$	-	-0.98	-3	V
	KRA567E		$V_O=-0.3V, I_O=-20mA$	-	-1.83	-3	
	KRA568E		$V_O=-0.3V, I_O=-20mA$	-	-1.22	-3	
	KRA569E		$V_O=-0.3V, I_O=-20mA$	-	-1.76	-2.5	
	KRA570E		$V_O=-0.3V, I_O=-2mA$	-	-2	-3	
	KRA571E		$V_O=-0.3V, I_O=-2mA$	-	-3.9	-5	
	KRA572E		$V_O=-0.3V, I_O=-1mA$	-	-1.64	-3	
Input Voltage (OFF)	KRA566E	$V_{I(OFF)}$	$V_{CC}=-5V, I_O=-100\mu A$	-0.3	-0.63	-	V
	KRA567E			-0.5	-1.15	-	
	KRA568E			-0.3	-0.67	-	
	KRA569E			-0.3	-0.82	-	
	KRA570E			-0.8	-1.68	-	
	KRA571E			-1	-3.09	-	
	KRA572E			-0.5	-1.17	-	
Transition Frequency	KRA566E 572E	f_T^*	$V_O=-10V, I_O=-5mA$	-	250	-	MHz
Input Current	KRA566E	I_I	$V_I=-5V$	-	-	-7.2	mA
	KRA567E			-	-	-3.8	
	KRA568E			-	-	-3.8	
	KRA569E			-	-	-1.8	
	KRA570E			-	-	-0.88	
	KRA571E			-	-	-0.16	
	KRA572E			-	-	-0.15	
Input Resistor	KRA566E	R_I	-	0.7	1	1.3	k Ω
	KRA567E			1.54	2.2	2.86	
	KRA568E			1.54	2.2	2.86	
	KRA569E			3.29	4.7	6.11	
	KRA570E			7	10	13	
	KRA571E			32.9	47	61.1	
	KRA572E			70	100	130	
Resistor Ratio	KRA566E	R_2/R_1	-	8	10	12	
	KRA567E			0.8	1.0	1.2	
	KRA568E			3.6	4.5	5.5	
	KRA569E			1.7	2.1	2.6	
	KRA570E			0.37	0.47	0.57	
	KRA571E			0.17	0.21	0.26	
	KRA572E			0.8	1.0	1.2	

Note : * Characteristic of Transistor Only.







KRA566E~KRA572E



KRA566E~KRA572E



KRA566E~KRA572E



KRA566E~KRA572E

